

## Pass

Contactless card to control security modes

Sold in packages of 3, 10, or 100 devices



### Convenient access to a system

- One Pass card can be paired with 13 Ajax systems.
- Set the name and access permissions for each card in the app.
- Modify Pass access permissions in real time: revoke, restrict, change, or expand users' access to security systems and groups.
- Every action is recorded in the event log, providing a history of system interactions.

### Sabotage resistance

- Copy protection.
- Triple DES encryption and AES hardware encryption with a 128-bit key.
- Authorization confirmation. The feature allows setting up two-factor authentication to control the system security modes, which requires both Pass and a passcode for authorization.

### Connection and configuration

- Pass is added to the system through the app by presenting the card to the keypad in the settings menu.
- Access settings can be changed remotely.

Tag. Same device,  
but in a different form.

Contactless key fob to control security modes.






**Superior, Fibra, and Baseline** product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

|   |   |   |   |
|---|---|---|---|
| <p><b>Compatibility</b></p> <p>KeyPad Plus Jeweller<br/>KeyPad TouchScreen Jeweller<br/>KeyPad TouchScreen Fibra<br/>KeyPad S Plus Jeweller</p>   | <p><b>Contactless authentication</b></p> <p><b>Communication technology</b><br/>DESFire®</p> <p><b>Operating standard</b><br/>ISO 14443-A (13.56 MHz)</p> <p><b>Encryption</b><br/>Triple DES encryption<br/>AES hardware encryption with a 128-bit key</p> | <p><b>Key features</b></p> <p><b>Assigned users</b><br/>Name and access permissions for each card in an Ajax app</p> <p><b>Ajax hubs</b><br/>up to 13 in memory</p> | <p><b>Sabotage protection</b></p> <p>Authentication<br/>Protection from signal interception</p> |
| <p><b>Enclosure</b></p> <p><b>Color</b><br/>Black<br/>White</p> <p><b>Dimensions</b><br/>86 × 54 × 0.8 mm<br/>3,39" × 2,13" × 0,02"</p> <p><b>Weight</b><br/>6 g<br/>0,2 oz</p> <p><b>Operating temperature range</b><br/>from -10 °C to +40 °C<br/>from 14 °F to 104 °F</p> <p><b>Operating humidity</b><br/>up to 75%</p> | <p><b>Complete set</b></p> <p>3, 10, or 100 devices<br/>(depending on the kit)<br/>Quick start guide</p>  |   |   |



For detailed information, scan the QR code or follow the link:  
[ajax.systems/support/devices/access-devices/](https://ajax.systems/support/devices/access-devices/)

-  [support@ajax.systems](mailto:support@ajax.systems)
-  [@AjaxSystemsSupport\\_Bot](https://twitter.com/AjaxSystemsSupport_Bot)
-  [ajax.systems](https://www.ajax.systems)