

## 10 Zone Master Call Controller c/w 300mA PSU (Surface Version) Part No. NC910S



## Overview

- Compatible with C-TEC's entire range of 800 Series field devices.
- Housed in an attractive surface mounting plastic enclosure measuring just 214mm x 178mm
- Two call levels standard (constant tone) and emergency (intermittent tone).
- Optional mute and call accept/reset buttons.
- 'Call Accept' functionality allows staff to send an intermittent call acknowledgment signal to calling zones to confirm help is on the way (dependent on wiring and field devices used).
- Includes a 12V 300mA PSU and 2 volt-free relay contacts which activate on a standard or emergency call.
- Innovative slide-in labelling system.
- Zones can be wired in 4 or 6 core (7/02) stranded security cable.
- Additional master controllers and expansion units available for use as repeaters on larger sites.
- Optional boxed PSUs c/w with space for a 12V VRLA battery available for sites where a standby battery facility is required.



## **More Information**

## **Technical Specifications**

T 01942 322744

F 01942 829867

Mains supply Internal power supply 230V 50/60Hz. (36mA max. current).

11V d.c. (300mA max. current when powered by Mains).



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom

E sales@c-tec.co.uk

W www.c-tec.com



Ouiescent current	0mA (none).
Alarm current	Determined by the number/type of field devices connected to the call controller/system.
Auxiliary relays	2 volt free relay contacts (NO/C/NC). Activate when a standard or emergency call is received by the controller. Both relays rated at 30V d.c. @ 1A.
Auxiliary inputs	External PSU Input: 9V-15V d.c. @ 400mA (suitable for use with an BF560-12 12V 2A boxed PSU which has space available for a 12V 7AH battery).
Indicators	Green Power on LED; 10 x red Zonal Alarm LEDs (lit steady for a Standard call, pulse for an Emergency call); Internal buzzer (on steady for any Standard call, intermittent for any Emergency call).
Controls	2 Buttons - (A) Reset or inactive ; (B) 'Mute' or 'Call Accept'. (Both buttons are link selectable). If Call Accept is selected indicators on relevant field devices will emit a slow intermittent to
Expansion connections	CONN2 allows the connection of 1 x NC910EF 10 Zone Expansion Unit or 1x NC920EF 20 Zone Expansion Unit.
Call acknowledgement functionality Yes.	
Product dimensions (mm)	214 W x 178 H x 70 D mm. Surface mounting.
Construction & finish	Plastic detachable lid and back box. RAL7035.
IP Rating	IP41.
Weight	1.27kg.
Operating conditions/temperature	$-5^{\circ}$ C to $+40^{\circ}$ C. Max. relative humidity 95% non-condensing.







