

Ajax Superior SpaceControl Jeweller

Wireless key fob with a panic button and control over security modes



This is a device of the Superior product line. Only accredited Ajax Systems partners can sell, install, and administer Superior products.

Ajax Superior SpaceControl Jeweller has a silicon overlay over the light indicators. This upgrade provides **improved protection against humidity**.

Arm

Arms the facility

Disarm

Disarms the facility

Night Mode

Activates Night Mode (switches devices to arming mode for perimeter security)

Panic

Notifies a security company and users of danger or emergency



Protection against accidental activation: double or long press



Jeweller communication technology

- Up to 1,300 m (4,250 ft) of radio communication in an open space
- Encryption and device authentication to prevent spoofing
- LED indication of button pressing



Flawless autonomy

- Up to 5 years of autonomous operation
- Pre-installed replaceable battery
- Notifications of low battery charge



Quick setup

- Pairing with a hub via QR code
- Remote control and configuration in the app
- It can be carried around in a pocket or on the key ring



<p>Compatibility with hubs and range extenders</p>  <p>For detailed information, scan the QR code or follow the link: ajax.systems/tools/devices-compatibility/?models=SC.S.J</p>	<p>Compliance with standards</p> <p>EN 50131 (Grade 2) PD 6662:2017 NFA2P SIA CP-01</p>	<p>Communication with a hub or range extender</p> <p>Jeweller communication technology</p> <p>Frequency bands 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the region of sales.</p> <p>Communication range up to 1,300 m up to 4,250 ft In an open space.</p>	<p>Power supply</p> <p>Battery 1 × CR2032 Pre-installed.</p> <p>Battery life up to 5 years</p>
<p>Installation</p> <p>Operating temperature range from –10 °C to +40 °C from 14 °F to 104 °F</p> <p>Operating humidity up to 95%</p> <p>Protection class IP32</p>	<p>Enclosure</p> <p>Color Black White</p> <p>Dimensions 65 × 37 × 10 mm 2.56" × 1.46" × 0.39"</p> <p>Weight 13 g 0.46 oz</p>	<p>Complete set</p> <p>Ajax Superior SpaceControl Jeweller 1 × CR2032 battery (pre-installed) Quick start guide</p>	



For detailed information, scan the QR code or follow the link:

ajax.systems/support/devices/ajax-superior-spacecontrol-jeweller



- ✉ support@ajax.systems
- 📍 @AjaxSystemsSupport_Bot
- 🌐 ajax.systems